BL Casambi Dimmer 4CH PWM

BL Casambi Dimmer 4CH PWM constant voltage

Article no.: 170924





TENDER TEXT

1-4 channel LED dimmer for constant voltage 24 VDC. Maximum total output 144W at 24 VDC (max. 6A). Input voltage 12-24 VDC. Radio control signal. PWM frequency 400Hz. Protection class IP20. Protection class III. dimensions LxWxH = 72.6x30x18mm BILTON LEDON Technology BL Casambi Dimmer 4CH PWM Article 170924 The controller BL Casambi Dimmer 4CH PWM is operated with Casambi . The controller and has an output voltage of 12-24 V . Dimension (L x W x H): 72.6 mm x 30 mm x 18 mm





BL Casambi Dimmer 4CH PWM

BL Casambi Dimmer 4CH PWM constant voltage

Article no.: 170924



MECHANICAL DATA

| Material | Kunststoff |
|--|--------------------------|
| Width of device [mm] | 30 |
| Height of device [mm] | 18 |
| Depth of device [mm] | 72.6 |
| Mounting method | sonstige |
| Colour | White |
| Surface protection | unbehandelt |
| Control signal | Casambi |
| Material quality | Thermoplast |
| Type of fastening | Befestigung mit Schraube |
| Applicable with movement sensor | yes |
| Applicable with transmission button | yes |
| Applicable with infrared button | nein |
| Applicable with presence indicator | yes |
| Applicable with time switch/timer | yes |
| Applicable with button | yes |
| Surface finishing | matt |
| Suitable for degree of protection (IP) | IP20 |
| App controll via Bluetooth | yes |

ELECTRICAL DATA

| Control signal | Casambi |
|---------------------|----------|
| Type of load | sonstige |
| Nominal power [W] | 144 |
| Nominal voltage [V] | 12 - 24 |

LIGHT TECHNICAL DATA

Light value memory yes

PACKAGING INFORMATION

| EAN | 4250716942033 |
|-----------------------|---------------|
| Article no. | 170924 |
| Net weight [g] | 45.1 |
| Gross weight [g] | 45.9 |
| Gross width [mm] | 100.0 |
| Gross height [mm] | 19.0 |
| Gross length [mm] | 140.0 |
| Customs tariff number | 8536500500 |
| Net width [mm] | 30.0 |
| Net height [mm] | 18 |

BL Casambi Dimmer 4CH PWM

BL Casambi Dimmer 4CH PWM constant voltage

Article no.: 170924



| Net length [mm] | 75 |
|-----------------|----|
| State of origin | FI |

SAFETY INFORMATION: Read the safety and installation instructions carefully and completely before commissioning. The operating instructions can be found at: www.better-light.at

DISCLAIMER OF WARRANTY: The technical information corresponds to the status at the time of printing and have been worked out to the best of our knowledge. However, errors and printing errors are reserved. Make sure that you always use the latest version of the data sheets. The latest data sheet can be found at: www.better-light.at