BL Casambi socket Plug and Play

BL Casambi Plug&Play socket 230V
Article no.: 171939



TENDER TEXT

Smart plug Casambi, black plastic, 150V, mesh network BILTON LEDON Technology BL Casambi socket Plug and Play Article 171939 The controller BL Casambi socket Plug and Play has a Casambi control signal. Furthermore, the controller operates with a nominal voltage of 220-240 V and has a protection rating. Dimensions (L x W x H): 45 mm x 85 mm x 55 mm

Casambi

© BILTON LEDON Technology | www.better-light.at
Gewerbepark Harham 2, 5760 Saalfelden | Austria | Phone: +43 6582 71164 | Mail: office@bltechnology.at
Version: 20261123 | Errors and printing errors are reserved.

BL Casambi socket Plug and Play

BL Casambi Plug&Play socket 230V
Article no.: 171939

MECHANICAL DATA

Material	Kunststoff
Width of device [mm]	85
Height of device [mm]	55
Depth of device [mm]	45
Mounting method	sonstige
Colour	black
Control signal	Casambi
Type of fastening	sonstige
App controll via Bluetooth	Yes

ELECTRICAL DATA

Voltage type	AC
Frequency [Hz]	50 - 60
Control signal	Casambi
Nominal power [W]	150
Nominal voltage [V]	220 - 240
Standby power consumption (solstandby) [W]	0.3

CONNECTION

Connection type	sonstige

TEMPERATURE TECHNICAL DATA

Ambient temperature during operating [°C]	- 20... + 45

SAFETY INFORMATION: Read the safety and installation instructions carefully and completely before commissioning. The operating instructions can be found at: www.better-light.at

DISCLAIMER OF WARRANTY: The technical information corresponds to the status at the time of printing and have been worked out to the best of our knowledge. However, errors and printing errors are reserved. Make sure that you always use the latest version of the data sheets. The latest data sheet can be found at: www.better-light.at

© BILTON LEDON Technology | www.better-light.at
Gewerbepark Harham 2, 5760 Saalfelden | Austria | Phone: +43 6582 71164 | Mail: office@bltechnology.at
Version: 20261123 | Errors and printing errors are reserved.