# Drive ECO Slim

#### BL DRIVE Eco Slim 60W 24V IP20 Power Supply Article no.: 172029

BETTER LIGHT



#### Output voltage range

### **TENDER TEXT**

Power supply, ECO Slim constant voltage. Max. output power 60W, maximum input voltage 220-240VAC, output voltage 24V, SELV, protection class IP20. Protection class II, dimensions L x W x H = 300 x 30 x 16 mm BILTON LEDON Technology power supply Drive ECO Slim Article 172029 The power supply can be used up to 0 - 60 W output power and 24 V output voltage. The supply voltage of the power supply is 176 - 264 V and has a IP20 protection class and protection class II . Dimension (L x W x H): 300.0 mm x 30.0 mm x 16.0 mm



# Drive ECO Slim

BL DRIVE Eco Slim 60W 24V IP20 Power Supply

Article no.: 172029



### MECHANICAL DATA

Housing	Kunststoffgehäuse
Width [mm]	30.0
Length [mm]	300.0
Height [mm]	16.0
Colour	White
Control signal	ohne
With overheating protection	yes
Suitable for outdoor use	nein
Degree of protection (IP)	IP20

## ELECTRICAL DATA

Protection class	II
Control signal	ohne
With overheating protection	yes
Imput voltage range [V]	176 - 264
Output voltage range [V]	24
Output power range [W]	0 - 60
Frequency supply voltage (range) [Hz]	50 - 60
Output current range [mA]	0 - 2500
Overload protection	yes
Standby power consumption (solstandby) [W]	0.5
Suitable for constant voltage	yes
Power factor	0.95
No dim function	yes

## TEMPERATURE TECHNICAL DATA

Ambient/storage temperature [°C]	- 40 + 85
Operation temperature at Tc [°C]	- 20 + 50
Lifespan at 20 °C [h]	80000

## PACKAGING INFORMATION

EAN	4250716951608
Article no.	172029
Net weight [g]	230
Gross weight [g]	230
Customs tariff number	85044083
Net width [mm]	300.0
Net height [mm]	16
Net length [mm]	30
State of origin	CN

© BILTON LEDON Technology | www.better-light.at

Gewerbepark Harham 2, 5760 Saalfelden | Austria | Phone: +43 6582 71164 | Mail: office@bltechnology.at Version: 20250713 | Errors and printing errors are reserved.

# Drive ECO Slim

#### BL DRIVE Eco Slim 60W 24V IP20 Power Supply

Article no.: 172029



3

SAFETY INFORMATION: Read the safety and installation instructions carefully and completely before commissioning. The operating instructions can be found at: www.better-light.at

DISCLAIMER OF WARRANTY: The technical information corresponds to the status at the time of printing and have been worked out to the best of our knowledge. However, errors and printing errors are reserved. Make sure that you always use the latest version of the data sheets. The latest data sheet can be found at: www.better-light.at