

BL Drive IP67 100W 24V

BL MW Power supply unit CV 90-305VAC 100W 24VDC 4000mA IP67
Article no.: 170203



Output voltage range



Output power range



Degree of protection (IP)

TENDER TEXT

Constant voltage power supply unit. Input voltage 90-305VAC. Maximum total power 100W (max. 4A). Output voltage 24VDC. Protection class IP67. Protection class I. Dimensions LxWxH = 220x68x38.8mm BILTON LEDON Technology power supply BL Drive IP67 100W 24V Article 170203 The power supply can be used up to 100 W output power and 24 V output voltage. The supply voltage of the power supply is 90 - 305 V and has a IP67 protection class and protection class III . Dimension (L x W x H): 220.0 mm x 68.0 mm x 38.8 mm



BL Drive IP67 100W 24V

BL MW Power supply unit CV 90-305VAC 100W 24VDC 4000mA IP67

Article no.: 170203



MECHANICAL DATA

Housing	Metallgehäuse
Width [mm]	68.0
Length [mm]	220.0
Height [mm]	38.8
Model	Static
Control signal	ohne
With overheating protection	yes
Suitable for outdoor use	yes
Degree of protection (IP)	IP67

ELECTRICAL DATA

Protection class	III
Voltage type	AC
Control signal	ohne
With overheating protection	yes
Input voltage range [V]	90 - 305
Output voltage range [V]	24
Output power range [W]	100
Output current range [mA]	4000
Type of dimming	not dimmable
Overload protection	yes
Suitable for constant current	yes
Suitable for constant voltage	yes
Suitable for DC-voltage (primary side)	yes

TEMPERATURE TECHNICAL DATA

Ambient/storage temperature [°C]	- 40 ... + 80
Operation temperature at Tc [°C]	- 40 ... + 70
Lifespan at 20 °C [h]	60000

PACKAGING INFORMATION

EAN	4250716936575
Article no.	170203
Net weight [g]	990
Gross weight [g]	1068
Gross width [mm]	90.0
Gross height [mm]	50.0
Gross length [mm]	290.0
Customs tariff number	85043180
Net width [mm]	60.0

BL Drive IP67 100W 24V

BL MW Power supply unit CV 90-305VAC 100W 24VDC 4000mA IP67

Article no.: 170203



Net height [mm]	35
Net length [mm]	205
State of origin	TW

SAFETY INFORMATION: Read the safety and installation instructions carefully and completely before commissioning. The operating instructions can be found at: www.better-light.at

DISCLAIMER OF WARRANTY: The technical information corresponds to the status at the time of printing and have been worked out to the best of our knowledge. However, errors and printing errors are reserved. Make sure that you always use the latest version of the data sheets. The latest data sheet can be found at: www.better-light.at