## BL Drive IP67 40W 24V

### BL MW Power supply unit CV 90-305VAC 40W 24VDC 1600mA IP67

Article no.: 170200







#### **TENDER TEXT**

Constant voltage power supply unit. Input voltage 90-305VAC. Maximum total power 40W (max. 1.6A). Output voltage 24VDC. Protection class IP67. Protection class I. Dimensions LxWxH = 171x61.5x36.8mm BILTON LEDON Technology power supply BL Drive IP67 40W 24V Article 170200 The power supply can be used up to 40 W output power and 24 V output voltage. The supply voltage of the power supply is 90 - 305 V and has a IP67 protection class and protection class III . Dimension (L x W x H):  $171.0 mm \times 61.5 mm \times 36.8 mm$ 









# BL Drive IP67 40W 24V

### BL MW Power supply unit CV 90-305VAC 40W 24VDC 1600mA IP67

Article no.: 170200



#### MECHANICAL DATA

Housing	Metallgehäuse
Width [mm]	61.5
Length [mm]	171.0
Height [mm]	36.8
Model	Static
Control signal	ohne
With overheating protection	yes
Suitable for outdoor use	yes
Degree of protection (IP)	IP67

### **ELECTRICAL DATA**

Protection class	III
Voltage type	AC
Control signal	ohne
With overheating protection	yes
Imput voltage range [V]	90 - 305
Output voltage range [V]	24
Output power range [W]	40
Output current range [mA]	1600
Type of dimming	not dimmable
Overload protection	yes
Suitable for constant current	yes
Suitable for constant voltage	yes
Suitable for DC-voltage (primary side)	yes

### TEMPERATURE TECHNICAL DATA

Ambient/storage temperature [°C]	- 40 + 80
Operation temperature at Tc [°C]	- 40 + 80
Lifespan at 20 °C [h]	60000

### PACKAGING INFORMATION

	47000
ticle no.	170200
et weight [g]	670
oss weight [g] 7	700
oss width [mm]	80.0
oss height [mm] 5	50.0
oss length [mm]	220.0
stoms tariff number 8	85043180
et width [mm] 5	50.0

# BL Drive IP67 40W 24V

#### BL MW Power supply unit CV 90-305VAC 40W 24VDC 1600mA IP67

Article no.: 170200



Net height [mm]	40
Net length [mm]	150
State of origin	CN

SAFETY INFORMATION: Read the safety and installation instructions carefully and completely before commissioning. The operating instructions can be found at: www.better-light.at

DISCLAIMER OF WARRANTY: The technical information corresponds to the status at the time of printing and have been worked out to the best of our knowledge. However, errors and printing errors are reserved. Make sure that you always use the latest version of the data sheets. The latest data sheet can be found at: www.better-light.at