

Panel Round

LED DRIVER 220-240V CC 1000mA 27-42VDC ON/OFF Panel Round

Article no.: 719245



ohne

Control signal

IP20

Degree of protection (IP)

II

Protection class

1000
mA

Output current range

TENDER TEXT

incl. connection cable for Panel Round600



Panel Round

LED DRIVER 220-240V CC 1000mA 27-42VDC ON/OFF Panel Round

Article no.: 719245



MECHANICAL DATA

| | |
|---------------------------------------|-------------------|
| Housing | Kunststoffgehäuse |
| Width [mm] | 44.0 |
| Length [mm] | 137.5 |
| Height [mm] | 23.0 |
| Model | Static |
| Control signal | ohne |
| With overheating protection | nein |
| Suitable for outdoor use | nein |
| Degree of protection (IP) | IP20 |
| Core cross section [mm ²] | 0,5 - 1,5 |

ELECTRICAL DATA

| | |
|--|-----------|
| Protection class | II |
| Control signal | ohne |
| With overheating protection | nein |
| Input voltage range [V] | 198 - 264 |
| Output voltage range [V] | 27 - 42 |
| Output power range [W] | 27 - 42 |
| Output current range [mA] | 1000 |
| Overload protection | yes |
| Standby power consumption (solstandby) [W] | 0.5 |
| Suitable for constant current | yes |
| Suitable for constant voltage | nein |
| Suitable for DC-voltage (primary side) | yes |
| No dim function | yes |

CONNECTION

| | |
|---------------------------------------|-----------|
| Core cross section [mm ²] | 0,5 - 1,5 |
|---------------------------------------|-----------|

TEMPERATURE TECHNICAL DATA

| | |
|---|---------------|
| Ambient/storage temperature [°C] | - 40 ... + 85 |
| Ambient temperature during operating [°C] | - 20 ... + 45 |

PACKAGING INFORMATION

| | |
|-----------------------|---------------|
| EAN | 4250716950656 |
| Article no. | 719245 |
| Customs tariff number | 85044083 |
| Net width [mm] | 44.0 |
| Net height [mm] | 23 |
| Net length [mm] | 137.5 |

Panel Round

LED DRIVER 220-240V CC 1000mA 27-42VDC ON/OFF Panel Round

Article no.: 719245



State of origin

CN

SAFETY INFORMATION: Read the safety and installation instructions carefully and completely before commissioning. The operating instructions can be found at: www.better-light.at

DISCLAIMER OF WARRANTY: The technical information corresponds to the status at the time of printing and have been worked out to the best of our knowledge. However, errors and printing errors are reserved. Make sure that you always use the latest version of the data sheets. The latest data sheet can be found at: www.better-light.at