Downlight Pure

LED DRIVER 220-240V CC 350mA 27-45VDC ON/OFF

Article no.: 729178





TENDER TEXT

incl. connection cable for FDL180









Downlight Pure

LED DRIVER 220-240V CC 350mA 27-45VDC ON/OFF

Article no.: 729178



MECHANICAL DATA

Housing	Kunststoffgehäuse
Width [mm]	44.0
Length [mm]	137.5
Height [mm]	23.0
Model	Static
Control signal	ohne
With overheating protection	nein
Suitable for outdoor use	nein
Degree of protection (IP)	IP20
Core cross section [mm²]	0,5 - 1,5

ELECTRICAL DATA

Control signal ohne With overheating protection nein Imput voltage range [V] 198 - 264 Output voltage range [V] 27 - 45 Output current range [mA] 350 Overload protection yes Standby power consumption (solstandby) [W] 0.5
Imput voltage range [V] Output voltage range [V] 27 - 45 Output current range [mA] Overload protection yes Standby power consumption (solstandby) [W] 198 - 264 27 - 45 000 27 - 45 000 000 000 000 000 000 000
Output voltage range [V] 27 - 45 Output current range [mA] 350 Overload protection yes Standby power consumption (solstandby) [W] 0.5
Output current range [mA] 350 Overload protection yes Standby power consumption (solstandby) [W] 0.5
Overload protection yes Standby power consumption (solstandby) [W] 0.5
Standby power consumption (solstandby) [W] 0.5
Suitable for constant current yes
Suitable for constant voltage nein
Suitable for DC-voltage (primary side) yes
No dim function yes

CONNECTION

Core cross section [mm²] 0,5 - 1,5

TEMPERATURE TECHNICAL DATA

Ambient/storage temperature [°C]	- 40 + 85
Ambient temperature during operating [°C]	- 20 + 45

PACKAGING INFORMATION

EAN	4250716953336
Article no.	729178
Customs tariff number	85044083
Net width [mm]	44.0
Net height [mm]	23
Net length [mm]	137.5
State of origin	CN

Downlight Pure

LED DRIVER 220-240V CC 350mA 27-45VDC ON/OFF

Article no.: 729178



SAFETY INFORMATION: Read the safety and installation instructions carefully and completely before commissioning. The operating instructions can be found at: www.better-light.at

DISCLAIMER OF WARRANTY: The technical information corresponds to the status at the time of printing and have been worked out to the best of our knowledge. However, errors and printing errors are reserved. Make sure that you always use the latest version of the data sheets. The latest data sheet can be found at: www.better-light.at