Downlight Pure

LED DRIVER 220-240V CC 450mA 9-45VDC DALI

Article no.: 729157





Oops - erwischt!

Hier folgt bald das gewünschte Bild.

TENDER TEXT

incl. connection cable for FDL380









Downlight Pure

LED DRIVER 220-240V CC 450mA 9-45VDC DALI

Article no.: 729157



MECHANICAL DATA

| Housing | Kunststoffgehäuse |
|-----------------------------|-------------------|
| Width [mm] | 44.0 |
| Length [mm] | 137.5 |
| Height [mm] | 23.0 |
| Model | dynamisch |
| Control signal | DALI / Switch |
| With overheating protection | nein |
| Suitable for outdoor use | nein |
| Degree of protection (IP) | IP20 |
| Core cross section [mm²] | 0,5 - 1,5 |

ELECTRICAL DATA

| Protection class | II |
|--|---------------|
| Control signal | DALI / Switch |
| With overheating protection | nein |
| Imput voltage range [V] | 198 - 264 |
| Output voltage range [V] | 9 - 45 |
| Output current range [mA] | 450 |
| Overload protection | yes |
| Standby power consumption (solstandby) [W] | 0.45 |
| Suitable for constant current | yes |
| Suitable for constant voltage | nein |
| Suitable for DC-voltage (primary side) | yes |
| Dimming DALI | yes |

CONNECTION

Core cross section [mm²] 0,5 - 1,5

TEMPERATURE TECHNICAL DATA

| Ambient/storage temperature [°C] | - 20 + 80 |
|---|-----------|
| Ambient temperature during operating [°C] | - 20 + 45 |

PACKAGING INFORMATION

| EAN | 4250716950632 |
|-----------------------|---------------|
| Article no. | 729157 |
| Customs tariff number | 85044083 |
| Net width [mm] | 44.0 |
| Net height [mm] | 23 |
| Net length [mm] | 137.5 |
| State of origin | CN |

Downlight Pure

LED DRIVER 220-240V CC 450mA 9-45VDC DALI

Article no.: 729157



SAFETY INFORMATION: Read the safety and installation instructions carefully and completely before commissioning. The operating instructions can be found at: www.better-light.at

DISCLAIMER OF WARRANTY: The technical information corresponds to the status at the time of printing and have been worked out to the best of our knowledge. However, errors and printing errors are reserved. Make sure that you always use the latest version of the data sheets. The latest data sheet can be found at: www.better-light.at